

## PRODUCT DATASHEET

### 20VA CHASSIS MOUNTED TRANSFORMER



Designed, Manufactured and tested in accordance with **BS3535**, **EN60742\***, **EN61558\***, **BS415**.

Dual Primaries. For use with 110, 220, 240 input  
4000V isolation Primary - Secondary

Comprehensive choice of Secondary Voltages.

Fully shrouded double section construction.

Weight	0.68	Kg
Typical Regulation	7.5	%
Frequency	50/60	Hz
Max Ambient	25	°C
Bobbin Material	UL94-HB Class "B" 130°C	

\*requires additional over-current /over-temperature protection.

Please see sheet 2 for part numbers.

## Part Numbers


Part No	Primary	Secondary	Recommended Secondary Fuse
D3647	0-110 0-110-130V	4.5+4.5V	2AT
D3648	0-110 0-110-130V	6+6V	1.6AT
D3649	0-110 0-110-130V	9+9V	1AT
D3650	0-110 0-110-130V	10V	2AT
D3651	0-110 0-110-130V	12+12V	0.8AT
D3652	0-110 0-110-130V	15+15V	0.63AT
D3653	0-110 0-110-130V	18+18V	0.5AT
D3654	0-110 0-110-130V	20+20V	0.5AT
D3655	0-110 0-110-130V	24+24V	0.4AT

Please see sheets 3 and 4 for dimensions, pin outs and connection information.

# PRODUCT DATASHEET

## 20VA CHASSIS MOUNTED TRANSFORMER


### Outline Drawing




# PRODUCT DATASHEET

## 20VA CHASSIS MOUNTED TRANSFORMER

### Connection Diagrams for D3647 110V Supply



### Connection Diagrams for D3647 - 220V supply



### Connection Diagrams for D3647 - 240V supply

